


Single Arm Pantograph Model: WBL 85 - Balfour Beatty Permaquip, SRS



Issue: 1/00 Made available: 25/05/00 Description no.: 4-991B.5111 Checked/approved: Santner



Contents

1.	Intro	duction		4
2.	Safet	•	ctions	
	2.2		g Out Earth	
	2.2	2.2.1		
		2.2.2	Safety Check	
		2.2.3	Repair and Maintenance Work	
		2.2.4	Transport	
3.	Tech	nical Da	ta	7
4.	Desc	ription (of Pantograph Components	8 to 11
	4.1		I Information	
	4.2		ral Components	
		4.2.1	Base Frame	
		4.2.2.	Lower Frame	
		4.2.3	Upper Frame	9
		4.2.4	Coupling Rod	9
		4.2.5	Pan Head	9, 10
		4.2.6	Parallel Guide Bar	10
		4.2.7	Air Bellow Drive	10
		4.2.8	Electrical Equipment	10
		4.2.9	Pneumatic Control Unit	10
		4.2.10	Compressed Air Chamber	11
		4.2.11	Compresse Air Signal Horn	11
		4.2.12	Ltach	11
5.	Asse	•		
	5.1		ıl Information	
	5.2		ort	
	5.3	Mountii	ng	12
	5.4		tion of Electrical Equipment	13
		5.4.1	High Voltage Connection	
	5.5	Mountii	ng of Pneumatic Air Connection	13
6.				
	6.1	Checkli	ist (also see # 10. "Adjustment")	14
7.	Main			
	7.1		ıl Information	
	7.2	Carbon	Current Collector Strip	16



	7.3	Bearings	16
		7.3.1 Grooved Ball Bearing, Ball Bearing Guide,	
		Ball Bushing	16
		7.3.2 Plain Bearing	
	7.4	Screw connections	17
		7.4.1 Fastening Moment for Screw Connections	
	7.5	Bellow Drive	
	7.6	Pneumatic Control Unit	
8.	Troul	bleshooting	18 to 19
	8.1	General Information	18
	8.2	Trouble Table	18 to 19
9.	Repa	irs	20 to 24
	9.1	General Information	20
	9.2	Dismounting of Pantograph from Top of Vehicle Roof	20
	9.3	Complete Disassembly of Pantograph	
	9.4	Repairs of component parts	
		9.4.1 Free Bearing of Base Frame and Upper Frame .	21
		9.4.2 Fixed Bearing of Base Frame, Coupling Rod and	1
		Upper Frame	22
		9.4.3 Pan Head	
		9.4.4 Bellow Drive	23
		9.4.5 Other Component Parts	
	9.5	Re-assembly after Complete Disassembly	23, 24
10.	Adju	stment Work	24 to 30
	10.1	General Information	24
	10.2	Adjustment of Coupling Rod and Resting Position	25
	10.3	Adjusting the Bellow Drive	26
	10.4	Adjustment of Contact Pressure	27
	10.5	Adjustment of Raising- and Lowering Time	28
	10.6	Adjustment Curve of Contact Pressure	
	10.7		
	10.8	Adjustment of Pan	31
	10.9	Adjustment of Contact Force Monitoring System	32
11.	Spar	e Parts	33 to 53
12.	Anne	e x	

Introduction

Single Arm Pantograph WBL 85 Balfour Beatty



1. Introduction

The single arm pantograph WBL 85 Balfour Beatty has been developed as an earthing pantograph which allows for a mobile electrical earthing of the catenary. Please note that the earthing pantograph should only be used as an additional earthing between two stationary earthing poles.

Our objective was to design and manufacture a simple, light weight, and easy to maintain, Pantograph. We further wanted to achieve an optimum in catenary contact behavior, even under the most basic overhead wire conditions, and combine with it a maximum of operating safety.

The last chapter contains the spare parts drawings. We kindly request you to describe the needed parts as accurate as possible and in accordance with this catalogue to assure a problem free order processing, and subsequent delivery.

Copyright by Schunk Bahntechnik Ges.mbH

All rights reserved.

This publication may not be reproduced, stored in a retrieval system, or transmitted in whole or in part, in any form or by any means, electronic, mechanical, photocopying, recording, or otherwise, without the prior written permission of the Copy Right Owner.

No liability for amy errors in this document.

We reserved the right to make any technical modifications.

Schunk Bahntechnik Ges.mbH Aupoint 23

A-5101 Bergheim, AUSTRIA phone: (0662) 459200-0 fax: (0662) 459200-1

email: office@schunk-group.at

Page 4 WBL 85-15kV



2. Safety Instructions

2.1 General



Warning:

Earthing with the aid of the WBL 85 earthing pantograph may only be carried out by authorsied personnel. For this reason the pantograph can only be activated by a key-switch, which is provided inside the car.

2.2 Carrying Out Earthing

- Check the overhead wire with a voltage indicator pole.
- Set up fixed earthing points at the ends of the working area in front of and behind the vehicle (distance of 5-6 km).
- Check again the overhead wire with a voltage indicator pole for correct earthing.
- If the overhead wire is voltage free, raise the pantograph up to the catenary

2.2.1 Safety Device

During raising and lowering of the pantograph, a signal horn sounds. As soon as the pantograph has reached the desired contact pressure for the appropriate earthing function, the acoustic signal ceases.

If the contact pressure falls below the preset level, then the signal sounds indicating that the earthing function of the pantograph has ceased.

2.2.2 Safety Check

(has be to made everytime from outhorised personnel when panto gets raised):

- Raise pantograph: check that horn sounds
- When carbonstrip contacts the catenary, check that the signal ends
- Wait about 10-15 sec
- Lower pantograph: check that horn sounds
- Raise panto into working position.

Technical Data

Single Arm Pantograph WBL 85 Balfour Beatty



2.2.3 Repair and Maintenance Work

Before carrying out any repair and maintenance work ensure that:

- the power to the catenary is switched off
- the pantograph is lowered.

After competing any repair and maintenance work ensure that:

- no tools or other loose parts have been left on the vehicle roof.

2.2.4 Transport



Attention

Persons are not allowed to stay underneath the pantograph during lifting and transportation.



3. Technical Data

Height in resting position	454 ±10 mm
Fixation distance - crossways	950 ±1 mm
Fixation distance longitudinal	800 ±1 mm
Min. working height over resting position	100 mm
Max. working height over resting position	2250 mm
Max. raising height over resting position	2460 ±50 mm
Total length	2484 ±10 mm
Lateral deflection at max. working height	
and a lateral force of 300 N, according to IEC 494	30 mm
Weight	~120 kg
Contact strip length	920 mm
Pan width	1600 ±10 mm
Pan height	300 ±5 mm
Contact strip width	35 mm
Contact strip material	Graphit-carbon
Rated voltage	25 kV
Static contact force120 N	N ±10 N(adjustable)
Rising time to max. working height	max. 10 sec.
Lowering time from max. working height	max. 10 sec
Supply pressure from vehicle	min. 5 bar
Electrical resistance of pantograph	5 mW
Max. speed for earthing function	10 km/h
Contact force monitoring:	by signal horn
Raising and lowering controlled bykey-switch inside vehicle (provided	by vehicle supplier




4. Description of Pantograph Components

4.1 General Information

Main features of the Single Arm Pantograph WBL 85 are:

- Low weight
- Simple construction
- Minimum maintenance
- Excellent contact behavior, even under basic catenary conditions
- Maximum operating safety

4.2 Structural Components



Page 8 WBL 85-15kV



4.2.1 Base Frame

The base is a welded structure of closed rectangular hollow steel profiles.

The following component parts are located on the base frame:

- Basic bearings for the lower frame
- Resting buffer for upper and lower frame
- Mounting fixtures for:
 - Air bellow
 - Coupling rod
 - High voltage hook-up
 - Pneumatic control unit
 - Signal horn

4.2.2. Lower Frame

The lower frame is a welded structure. Its seating is located on the base frame.

The following component parts are mounted to the lower frame:

- Cam disks with suspension fixture for the bellow-drive ropes
- Parallel guide bar

4.2.3 Upper Frame

The upper frame is a welded structure made of seamless tubes. Necessary lateral stability is achieved through a cross wire-rope construction.

Attached to the upper frame are the following component parts:

- Pan head
- Coupling rod
- Lower frame
- Bearing blocks for the knuckle joint bearings

4.2.4 Coupling Rod

The coupling rod consists of two individually welded round-tubes. Both tubes are then connected through a control element. Through this control element the geometry of the pantograph will be adjusted and fine tuned.

4.2.5 Pan Head

The pan is fixed to the upperframe of the pantograph by means of a pantube. Fitted to the pan tube are two levers which at the other ends take up the carbon strip via a collectorstrip support. These levers guide the collectorstrip when moving vertically.

Description

Single Arm Pantograph WBL 85 Balfour Beatty



The collectorstrip is raised up against weight and contact pressure by means of leaf springs. As the carbon strip presses against the catenary with increasing force, it tensions up until the spring system is arrested by an adjustable stopper.

On the pan, a monitoring valve is located which applies pressure to a pneumatic signalhorn (located on the baseframe) – as long as the correct contact force between carbonstrip and catenary is not reached. When the pre-set contact pressure is achieved, the carbon strip tensions against the stopper, the monitoring valve switches over, the horn is no longer pressured, and the signal ceases.

In addition, the following parts are located on the pan:

- Shunts for the connection between contact strip and upperframe
- 3/2 way monitoring valve

4.2.6 Parallel Guide Bar

The parallel guide bar prevents the pan head from rotating,. It holds the collector strip in a horizontal position.

4.2.7 Air Bellow-Drive

The pneumatic bellow drive allows the pantograph to rise. It is mounted between the base frame and the lower frame. A pneumatic line connects the bellow drive with the valve control unit. The contact pressure as well as the raising and lowering time is adjusted through the valve control system unit.

4.2.8 Electrical Equipment

All bearing locations are by-passed by shunt connectors. These prevent the current from flowing through the bearings. The shunts are consisting of flexible copper cables with clamped end pieces. The current connectors are greased with copper grease to archieve good conducting properties between the shunts and the frame parts.

4.2.9 Pneumatic Control Unit

The pneumatic control unit is fitted inside a switching box which is fixed on the baseframe.

The pneumatic control unit ensures pneumatic adjustment of the pantograph like contactforce and raising- and loweringtime.

Page 10 WBL 85-15kV



The main components of the valve control unit are:

- Airfilter with condensate seperator
- Pressure regulation valve
- Throttle valve
- Security valve

There is also a pneumatic conduction for the latch, which is leading through the switchingbox.

4.2.11 Compressed Air Chamber

A compressed air chamber is integrated into the pneumatic feed to the signalhorn, forming a pressure air reservoir, ensuring that – in the event of a fall in air pressure in the feed to the signal horn (when the pantograph is lowered or when a loss of air pressure occurs in the feed as a result of a fault) – sufficient air volume is still available to enable the signal horn to sound for the appropriate duration.

4.2.12 Compressed Air Signal Horn

A signal horn is attached to the baseframe. The horn sounds during the raising and lowering operations and when there is too little contact pressure onto the catenary. As soon as the pantograph has reached the required contact pressure for correct earthing function, the acoustic signal ends. A monitoring valve on the pan controls the signal horn operation.

4.2.13 Latch

The latch ensures, that the pantograph is secured in restingposition, when it is out of service. The pneumatic circuit inside the vehicle is layed out in a way, that the latch opens before the the airbellow get under pneumatic-pressure for raising the pantograph.




5. Assembly

5.1 General Information

The Single Arm Pantograph is manufacturer-adjusted according to your system's requirements.

5.2 Transport



For transportation and lifting purposes fix panto only on fixing points (1, 2, 3, 4) of the base frame.



Attention:

No one admitted underneath the pantograph during lifting and transportation!

Caution: Do not damage coating during transportation!

5.3 Mounting

The base frame has to be mounted tension free onto the vehicle roof. The base pipe of the lower frame has to be horizontal. If needed washers may be installed underneath the fixing lappets.


Page 12 WBL 85-15kV



5.4 Installation of Electrical Equipment

5.4.1 High Voltage Connection

The high voltage earthing has to be made on the connecting strap (1) connection. The connecting spot needs to be well greased with conducting grease.




5.5 Mounting of Pneumatic Air Connection

The pneumatic connection between vehicle and pantograph has to be accomplished on the connections (1) and (2). Both connection have a 1/4" inside thread.

Connection (1): Connection for pantograph-airbellowdrive

Connection (2): Connection for latch





6. Start - Up

6.1 Checklist (also see # 10. "Adjustment")

Check before start-up:

- Screw connections of high voltage hook-up, and verify that they are well greased
- O Contact pressure of pantograph (120N, ±10N)
- O Raising and Lowering time to be in according with technical data
- O Check signal horn for proper function (see 2.2)

Page 14 WBL 85-15kV



7. Maintenance

7.1 General Information

The Single Arm Pantograph WBL 85 requires less maintenance. At the regular maintenance intervals of the vehicles, the following procedures are recommended:

During each inspection (max. 10000 km):

- O Inspection of carbon strips (breaks, wear).
- Inspction of horns.
- O Check proper function of signalhorn and contact force monitoring system.

Every year:

- Visual inspection of screws and shunts.
- O Visual inspection of cable of raising mechanism, if needed, grease with TOP 2000 of company AGIP Schmiertechnik.
- Inspection upward force, adjust, if necessary.
- O Inspection easy motion of bearings, pan head springs, etc.
- Pneumatic equipment for leakages.

After max. 3 years:

- O Grease the ends of the tow-rope with TOP 2000 of AGIP Schmiertechnik.
- Replace shunts.

After every 8 to 10 years and on any main inspection (max. after 2000000 km / 1250000 miles):


- Change all ball bearing.
- Inspect for corrosion, if necessary replace coaling.
- Change rubber bumpers on base frame.
- Change leaf springs of pan head.
- O Change cable of raising mechanism.
- Inspect/change of valve control unit.
- Change plain bearings.
- O Replace all air tubes.
- Inspect/replace air bellow drive.
- O Replace 3/2-way monitoring valve on pan head.



7.2 Carbon Current Collector Strip

The carbon strip need to be checked for damage and wear at every visual inspection. As a guide line to determine the intervals between visual inspections, please consider:

- Anticipated operating and wear life.
- Extreme weather conditions (ice, snow, rain, etc).



Latest with a remaining carbon height of 2 mm the carbon strips should be replaced.

7.3 Bearings

7.3.1 Grooved Ball Bearing, Ball Bearing Guide, Ball Bushing

The grooved ball bearings are to be cleaned and greased during every main inspection, and tested for flexibility of motion and bearing play. If motion of bearings is slow, determine the reasons (e.g. misalignment, bent component part, locked up stress, etc.). Damaged grooved ball bearings are to be exchanged. The space of the ball bearings needs to be filled completely with

grease TOP 2000 of AGIP Schmiertechnik

in order to avoid condensation.

7.3.2 Plain Bearing

All plain bearings of pantograph WBL 85 are maintenance free. The plain bearings are either:

- Teflon-coated bronze bushings or
- Plastic bushings

If plain bearings are slow, reason of slowness has to be determined and eliminated. Damaged plain bearings need to be exchanged. Dirty plain bearings have to be cleaned. We recommend to grease bearings with

grease TOP 2000 of AGIP Schmiertechnik.

Page 16 WBL 85-15kV



7.4 Screw Connections

All mounting screws are to be checked for damage and tight fit, especially:

- Mounting screws for carbon strips.
- Pan Head connections.

Hex nuts according DIN 985 must be replaced by new ones after dismounting!

7.4.1 Fastening Moment for Screw Connections

Thread	Fastening Moment	Thread	Fastening Moment	Thread	Fastening Moment
M3 M4 M5 M6	1,1 Nm 2,6 Nm 5,1 Nm 8,8 Nm	M8 M10 M12 M14	21,4 Nm 44,0 Nm 74,0 Nm 119,0 Nm	M16 M20	183,0 Nm 370,0 Nm

7.5 Bellow Drive

The bellow drive is maintenance free.

Check bellow drive for operation during each main inspection by lifting and lowering the pantograph. If needed, replace damaged or bent parts.

The cables are to be greased with TOP 2000 of AGIP Schmiertechnik, if necessary.

7.6 Pneumatic Control Unit

During each main inspection the safety valve needs to be tested by increasing the pressure through the pressure regulator.

After completed test, adjust contact pressure to required level.



8. **Troubleshooting**

8.1 **General Information**

Adjustment works are referred to in the "Adjustment Work" chapter.

8.2 **Trouble Table**

Defect	Reason(s)	Correction			
Pantograph does not rise or lower.	Air bellow damaged.	Check air bellow, exchange broken air bellow. (also see defect: Bellow drive defective)			
	Cable torn.	Replace cables. (also see defect: Cable torn)			
	Pneumatic control unit defective.	Exchange valve unit.			
	Pneumatic tube defect.	Replace pneumatic tube.			
	Inner friction of panto is too high.	Check pantograph for damages, and eliminate damages.			
		Replace defective bearings			
Uneven wear of carbon strip.	Parallel guide bar is poorly adjusted.	Adjust turning capacity of pan head. (also see # 10.7, adjust turning capacity of pantograph head)			
Cable torn.	Bellow drive is improper adjusted; bellow does not expand straight-lined.	Replace cables, adjust bellow to achieve straight expanding line. (also see # 10.3, adjusting the bellow drive)			
	Cables are not greased	Replace cables and grease in area of cam disk with non-water-soluble grease.			
Bellow drive defective.	Screws are loose.	Tighten screws.			
	Hose line leaking.	Exchange leaking hose with new hose line.			
		WBL 85-15kV			

Page 18



Single Arm Pantograph WBL 85 Balfour Beatty

Troubleshooting

Defect	Reason(s)	Correction		
	Bellow cylinder leaking.	Exchange bellow cylinder; find reason for leakage and check bellow joints.		
Excessive air leakage.	Pressure-regulator defective (normal air leakage of pressure regulator = 0,5 l / min.).	Exchange pressure regulator.		
Increase of contact pressure without previous adjustment of pressure regulator.	Pressure regulator defective.	Exchange pressure regulator.		
Signal horn for contact force monitoring does not	Monitoring valve on pan defective	Replace valve		
sound during raising or lowering.	Restrictor in compressed air line defective	Replace restrictoror		
	Compressed air line defective	Replace air hose		
	Signal horn defective	Replace signal horn		
Signal horn sounds while pantograph in operation	Contact force incorrectly set.	Check contact force and re-adjust setting		
(on catenary)	Monitoring valve on pan poorly set	Adjust setting of valve		
	Pan head spring stop incorrectly set	Re-adjust setting		
	Excessive inner friction of pantograph	Find cause of excessive friction and replace defective component		
	Pan lever bearings are stiff.	Replace bearings. Check pan levers for deformation and replace if necessary.		



Repairs 9.

9.1 **General Information**

Prior to disassembling the pantograph, please make familiar with the relationship of the individual component parts by studying the drawings (chapter #11).

Deformed component parts are to be disassembled before adjusting.

The alignment of the bearings is only accurately measurable on a measuring table.

9.2 Dismounting of Pantograph from Top of Vehicle Roof

	Lower pantograph into lowest resting position.									
	Make sure that current in catenary is switched off.									
	Detach electrical connection between pantograph and vehicle.									
	Unscrew pneumatic connections to vehicle.									
	Secure upper frame to base frame (e.g. with a rope)									
	Secure pantograph at the transport fixing points. (see # 5.2 Transport Chapter).									
	Detach pantograph from fixing-supports on vehicle.									
	Lift pantograph off vehicle roof. Attention: No persons is allowed to be underneath the transported pantograph.									
Com	plete Disassembly of Pantograph									

9.3


	, proceeding of the same graphs
	Mount pantograph on suitable resting feets to protect air bellow and signal horn.
	Lower pantograph into lowest resting position.
	Detouch signal horn from base frame.
	Detach air conditions.
	Detach shunts and carbon strips.
	Detach parallel guide bar.
	Detach pan head from upper frame
	Detach coupling rod from upper frame and base frame.
	Detach upper frame from lower frame.
	Detach air bellow drive.
	Detach lower frame from base frame.
	Detach latch from base frame.
	Detach pneumatic control unit from base frame and compressed air chamber.

Page 20 WBL 85-15kV



9.4 Repairs of Component Parts

9.4.1 Free Bearing of Base Frame and Upper Frame




Instructions:

- □ Remove both cover plates (1) (e.g. using a screwdriver).
- Push bearing housing (5) out of bearing block by means of a sleeve, which only rests on the outer ring of the grooved ball bearing.
- □ Detach both retaining rings (4) with retaining ring pliers.
- □ Push bearing shaft (2) out of grooved ball bearing (3), clean, check for movebility and bearing play, and replace if necessary.
- Assembly of bearings vice versa pack space between grooved ball bearings with grease TOP 2000 of AGIP Schmiertechnik.



9.4.2 Fixed Bearing of Base Frame, Coupling Rod and Upper Frame



Instructions:

- Remove both cover plates (1) (e.g. using a screwdriver).
- □ Detach both retaining rings (4) with retaining ring pliers.
- Push bearing housing (5) out of bearing block by means of a sleeve, which only rests on the outer ring of the grooved ball bearing.
- □ Push bearing shaft (2) out of grooved ball bearing (3), clean, check for movebility and bearing play, and replace if necessary.
- Assembly of bearings vice versa pack space between grooved ball bearings with grease TOP 2000 of AGIP Schmiertechnik.

9.4.3 Pan Head


- □ Detach 3/2 way monitoring-valve from pantube
- □ Detach pneumatic screw-joints and blind from 3/2 way-valve
- Detach collectorstripsupport from levers
- □ Detach axle and springroll from collectorstripsupport
- Detach levers from pantube
- Detach leafsprings and underlayingsprings from pantube
- Detach axles and plainbearings from levers and pantube
- Detach horns and tubs from collectorstrip

Page 22 WBL 85-15kV



9.4.4 Bellow Drive

Detach bellow drive, check parts and replace defective ones.





Caution is required during assembly of the bellow drive that the axle joint is positioned correctly. The axle joint prevents "buckling" of the bellow.

Mount of bellow to pantograph.

Caution: Do not overtorque the cables, as it otherwise may jam the bellow.

☐ Tighten both ropes evenly and adjust bellow (see # 10.3 chapter Adjust Bellow).

9.4.5 Other Component Parts

If the pantograph is damaged, all components need to be checked very carefully and replaced if needed.

9.5 Re-assembly after Complete Disassembly

If the pantograph had been completely disassembled, the re-assembly is to be conducted as follows:

- ☐ Mount free bearings and fixed bearings for lower frame as well as rubber puffer.
- Attach cam discs to lower frame.
- Mount lower frame to base frame.
- Attach drive cables to bellow and secure with lock nut
- Mount elevitation stop to bellow.

Repairs

Single Arm Pantograph WBL 85 Balfour Beatty



Attach bellow drive to base frame.
Mount drive cables to lower frame and secure with lock nuts.
Assemble coupling rod (bearing, calibration) and mount to base frame.
Install bearings of upper frame.
Mount upper frame to lower frame, and coupling rod to upper frame.
Mount diagonal cables to upper frame and tighten (caution during tightening, upper frame may not distort).
Attach plainbearings and axles into levers.
Mount levers to pantube.
Screw leafsprings and underlayingspring onto pantube.
Mount axle and springroll on collectorstripsupport.
Mount collectorstripsupport on levers.
Attach pneumatic screw connections and blind to 3/2 way-valve.
Screw 3/2-way-monitoring-valve to pantube.
Mount horns and tubs to collectorstrip.
Mount collectorstrip complete with horns on collectorstripsupport.
Attach bearing for parallelguide to pantube.
Mount panhead on upperframe.
Assemble parallel guide bar.
Attach parallel guide bar between lower frame and pan head mount.
Mount latch on base frame.
Mount shunts.
Screw pneumatic control unit to baseframe.
Screw compressed air chamber to baseframe.
Mount signalhorn on baseframe.
Install pneumatic conductions.
Intermediate Check - verify tightness of all screws.
Adjust pantograph (see chapter 10, Adjustment Work).
Final inspection on pantograph.
Mount pantograph to vehicle roof.
Establish electrical connection between pantograph and vehicle.
Establish pneumatic connection from panto to vehicle.
Before operation follow instructions of checklist in chapter 6.1.



Caution: No tools or loose parts may remain on vehicle roof.

Page 24 WBL 85-15kV



10. Adjustment Work

10.1 General Information


Each pantograph had been calibrated by the manufacturer.

Adjustment works are to be carried out in the following order:

- Adjust coupling rod and resting position
- Adjust contact pressure
- Adjust curve of contact pressure
- Adjust turning of pan head
- Adjustment of pan
- Adjustment of contact force monitoring system

10.2 Adjustment of Coupling Rod and Resting Position

The resting position of the pantograph is adjusted through the coupling rod (1).



Instructions:

- Adjustments are made through the rod adjuster (6) on the coupling rod (1).
- □ After adjustments tighten lock nuts (5).

Check: Lower Pantograph. Lower frame (2) and upper frame (3) have to rest on rubber bumper (4).




Through changing the length of the coupling rod the geometry of the pantograph has changed. Therefore check the curve of the contact pressure and adjust if necessary.



10.3 Adjusting the Bellow Drive

Check: Lift and lower the pantograph. Parallelism of the connection plate (1) to the base shaft (2) of the lower frame has to be assured during the raising and lowering procedures.



If fine tuning is required, proceed as follows:

- □ Lower pantograph, bellow has to be completely without pressure.
- □ Loosen lock nuts (3) on both drive wire ropes.
- Adjust length of wire ropes by means of hexagonal nuts (4) until parallelism between the connection plate (1) and base shaft (2) is accomplished.
- □ Verification through raising and lowering of pantograph.
- Secure again with lock nuts.
- ☐ Final inspection of the fine tuning through raising and lowering of the pantograph.

Page 26 WBL 85-15kV



10.4 Adjustment of Contact Pressure

The medium contact pressure is 120 N.

After each replacement of carbon strip the contact pressure needs to be verified. Contact pressure may be measured with a spring scale or with the SCHUNK Pantograph Contact Pressure Measuring Gauge KM 11.

Measurement of contact pressure with spring balance:

Value 1: Measuring of contact pressure from highest working position with

slow descending motion into resting position.

Value 2: Measuring of contact pressure from resting position with slow

ascending motion into the highest working position.


Results: (Value 1 + Value 2) = Average Value = Contact Pressure

2

Friction: Difference of contract pressure between Value # 1 and Value # 2

(ideal value lower than 20 N)

If the difference of the contact pressure is greater than 40 N, determine the reason (e.g. defective component part, dirt in the bearings, etc.) and have it corrected.



The calibration is done by means of the regulating screw (2) at the pressure regulator (1) on the pneumatic guide system.


Adjust through:

turning clockwise = increase contact pressure
 turning counter-clockwise = decrease contact pressure



10.5 Adjustment of Raising- and Lowering Time

The adjustment of the raising and lowering time can be made by turning the regulation screw (2) of the throttle valve (1).



Adjustment:

- □ For increasing the raising- and lowering time turn regulation screw (2) into clockwise direction
- □ For decreasing the raising- and lowering time turn regulation screw (2) against clockwise direction


The max. raising- and lowering time up to max. working height is 10 sec.

Page 28 WBL 85-15kV



10.6 Adjustment Curve of Contact Pressure

The contact pressure should be nearly constant over the entire working range.



Instructions:

- □ Loosen the four screw connections (3).
- □ Calibration is done by means of adjustment screw (1) on the cam disc (4) of the lower frame.

Adjustment through:

- Turns clockwise = contact pressure increases in the lower working range
- Turns counter clockwise = contact pressure decreases in the lower working range


Adjustment is required until curve of contact pressure is nearly constant over the entire working range. Verification with spring balance or with the SCHUNK pantograph contact pressure measuring gauge KM 11.

Then tighten lock nuts and screw connections.



10.7. Adjust Turning of Pan Head

The adjustment of the panheadturning has to be made in medium workingheight of the pantograph (about 1100 mm above resting position). By means of the adjustment on the parallelguide, the contact strip surface (A) has to be adjusted to an exact horizontal position. Measurement can by made by means of a spirit-level.




Instructions:

- Remove the parallel guide bar from lower frame.
- □ Loosen lock nut (2).
- Adjustment is accomplished through screwing in or screwing out of the parallel guide bar at the rod end (1).
- ☐ After adjustment tighten lock nut and re-check adjustment.

Page 30 WBL 85-15kV



10.8 Adjustment of Pan




Instructions:

- □ Loosen lock nut (1), turn in regulating screw (2) completely.
- ☐ Hang spring balance onto contact strip (3) and pull down vertically with 90 N.
- Screw out regulating screw (2) until screw sits against lever (4).
- □ Tighten lock nut (1).
- □ Allow pan to release
- □ Check: Pull down contact strip vertically again by means of spring balance, and check whether vertical movement of contact is blocked by screw (2) exactly at a force of 90 N.



10.9 Adjustment of Contact Force Monitoring System



Instructions:

- □ Loosen securing screws (1) of 3/2-way valve
- □ Slide valve (5) down all the way
- □ Switch pantograph in raising position
- Apply load on contact strip (2) vertically, until lever (3) contacts the regulating screw (4). (The pan must have been adjusted before see 10.8.)
- □ Slide the valve (5) upwards over oblong holes until the lifter of valve (5) is actuated by the pan spring, causing the signal of the compressed air horn to cease.
- □ Tighten screws (1).
- □ Check: Tension and release contact strip. As soon as the lever (3) hits the regulating screw (4), the acoustic signal must cease. Whenever lever (3) moves away from screw (4), the signal horn must sound.

Page 32 WBL 85-15kV




11. Drawings of Component Parts

In your order please specify:

- Type and serial number of pantograph
- Drawing number, item number on drawing, name and number of component part
- Required quantity

The component parts are shown on the following drawings annexed hereto:

1-9910.4961	Pantograph WBL 85
1-B14.2022	Bellow drive
1-9915.4985	Pneumatic control
1-9918.4957	Pan Head
1-KL19.2700	Latch
3-L03.1977	Upper frame bearing
3-L01.1973	Base frame bearing



1 2		2 3		3 4 5					6	7	6						
Po	os.	D	Mer C	nge B	A	Ein- heit	Benennung			Sachnum Normbezeich	mer hnung	\	Verkstoff	Gewicht kg/Einheit	Bemerk	kung	
	1				1	Stk	Grundrahmen			Zg. Nr. 1-9911.498 10-01-4982	82						
	2				1	Stk	Unterschere			Zg. Nr. 1-7555 S10-02-7555							
,	3				1	Stk	Oberschere			Zg. Nr. 1-7556 11-03-7556							
	4				1	Stk	Balgantrieb			Zg. Nr. 1-B14.202. 510-04-2022	2						
,	5				1	Stk	Ventilsteuerung			Zg. Nr. 1-9915.498 S10-05-4985	85						
	6				1	Stk	Kuppelstange			Zg. Nr. 2-K16.469 10-06-4699	9						
	7				1	Stk	Parallelführungs	star	nge	Zg. Nr. 2-7544 60-07-0106					Ohne P. 4,5	5,6,7,10,11	
(8				1	Stk	Wippe			Zg. Nr. 1-9918.49. S10-08-4957	57						
	9				1	Stk	Niederhalteklink	е		Zg. Nr. 1-KL19.270 S10-16-2700	00				Ohne P. 2	0,23	
7	0				1	Stk	Oberscherenlage	er		Zg. Nr. 3-L03.197 S10-03-1977	7						F
Í	11				1	Stk	Basislager			Zg. Nr. 3-L03.197. S10-01-1973	3						
1	2				2	Stk	Wippenlagerung			Zg. Nr. 4-L18.269 S10-08-2697	7						
1	3				2	Stk	Seil			Zg. Nr. 3-7609 11-04-7609							
1	4				2	Stk	Diagonale für Ob	ersc	chere	Zg. Nr. 3-7574 11-03-7574							
1	5				2	Stk	Auflagepuffer			Zg. Nr. 4-G01.254 46-02-4772	4						
1	6				1	Stk	SM-Anschlagpu	ıffer		M10 Form Nr. 25 46-03-1050	481						
					len Menge	nspalten			St. Ausg.	Aenderung/Datum							
А	WE Pe	3L 85 ermaqu	Balfou ip, SR	ır Bea S	tty			Α	A	Pos. 8 /01.00							
В											Bearb. 14.12.99. S Gepr. 14.12.99 P	antner ardeller	Stromabneh Pantograph		85		
С											Norm. Schunk	(schynk)	1-9910.496	1		Blatt	-
D											Bahntechnik Salzbu	GMbH Ers.	S10−00−49 f.	61		01 04 BI	


1		2			3	4			5		6	7	6
Pos	s. D	Men C	ge B	A	Ein- heit	Вепеппи	ng		Sachnummer Normbezeichnung		Werkstoff	Gewicht kg/Einheit	Bemerkung
3.	3			1	Stk	Doppelreduziei	rnipp	el	2511-1/4-1/2 28-30-1214	Ms ver	nickelt		
34	4			2	Stk	L-Schwenkvers	schra	ubung	1525-10/8-1/4 28-23-1012	Ms ver	nickelt		
33	5				m	Druckluftschla	uch		ø10/8 29-04-1008	PU-sc	hwarz		
36	6			2	Stk	Sechskantschi	raube	9	M10x95 DIN 931 21-10-0953	A2-70)		
37	7			15	Stk	Scheibe			A 10,5 DIN 125 32-10-0003	A2			
38	8			2	Stk	Schrumpfschlo	auch		19/6 Länge = 70 mm 42-01-0196	selbstk	(lebend		
35	9			1	Stk	Kabelbinder			5x250 43-05-2508	schwai	Z		
40	0			4	Stk	Sechskantschi	raube	9	M10x25 DIN 933 20-10-0253	A2-70)		
4	1			1	Stk	T-Stück 1/4'	T-Stück 1/4" Ger. Einschraubverschr. Typenschild		2070-1/4-1/4 28-36-1212	Ms ver	rnickelt		
42	2			1	Stk	Ger. Einschrau			GE 12 PLR 1/4" 28-01-1212	verzink	verzinkt		
4.	3			1	Stk	Typenschild			Zg. Nr. 4-G01.2545 60-16-0036				
44	4				m	Druckluftschla	uch		Ø6/4 29-05-0604	Pu-sc	hwarz		
45	5			20	Stk	Kabelbinder			7,8x365 43-07-3658	UV-be	ständig, schwarz		
46	6			20	Stk	Montageschell	e		CH-B7 43-07-0000	PU			
4	7	1 Stk Winkelversc		Winkelverschro	ubur	ng	1550-6/4 28-25-0620	Ms ver	rnickelt				
48	8			1	Stk	Druckluftschla	uch		Zg. Nr. 3-B14.4785 29-02-4785				
		Ango	aben zu d	len Menge	nspalten	1	Zg. Aŭsg	St. Ausg.	Aenderung/Datum				
А	WBL 85 Permaqu	Balfou ip, SR	r Bea S	tty			A	Α	Pos. 8 /01.00				
В									Bearb. 14.12.99 Gepr. 14.12.9		Stromabneh. Pantograph	mer WBL 8 WBI 85	5
С									Norm. Schun	schynk	1-9910.496	1	Blatt
D										ik GMH L	S10-00-49 Ers.f.	51 	03 04 Bl.

| | |


	1		2			3	4			5			6	7	6
Р	'os.	D	Menç C	де В	A	Ein- heit	Benenni	ung		Sachnum Normbezeid	nmer chnung		Werkstoff	Gewicht kg/Einheit	Bemerkung
	17				2	Stk	Niro-Achse			Zg. Nr. 4-7605 10-01-7605					
	18				1	Stk	Druckluftkess	el MD	S-2	L 149.1010 60-05-0118					
	19				8	Stk	Stromband			Zg. Nr. 4-500.46. 510-14-4630	30				
2	20				1	Stk	Adapter f. Para	llelführu	ungsst	Zg. Nr. 3-2617.22 S10-07-2262	262				
4	21				1	Stk	Sechskantsch	ıraube)	M8x50 DIN 931 21-08-0503		A2-70)		
2	22				21	Stk	Sechskantmu	tter		M8 DIN 985 30-08-0023		A2-70)		
2	23				12	Stk	Sechskantmu	tter		M14 DIN 934 30-14-0003		A2-70)		
2	24				1	Stk	Drucklufthorn	400	mm	093162202 60-05-0119		A2			
2	25				1	Stk	Rückschlagve	ntil 1,	/4"	VNR-843-07 55-23-0012		Ms vei	rnickelt		
7	26				2	Stk	Splint			3x25 DIN 94 38-03-0253		A2			
Ž	27				22	Stk	Scheibe			A 8,4 DIN 125 32-08-0003		A2			
2	28				7	Stk	Sechskantmu	tter		M10 DIN 985 30-10-0023		A2-70)		
2	29				16	Stk	Sechskantsch	ıraube)	M8×25 DIN 933 20-08-0253		A2-70)		
	30				1	Stk	Reduzierung 1,	/2"a-	1/4"i	2531-1/2-1/4 28-30-1412		Ms ver	rnickelt		
	31					m	Druckluftschlo	auch		Dekoron Ø6 29-10-0604		Polyäti	hylen-Al		
	32				1	Stk	L-Schwenkver.	schrau	ıbung	1525-6/4-1/4 28-23-0612		Ms vei	rnickelt		
		-	Anga	ben zu c	den Menge	nspalten		Zg. Ausg.	St. Ausg.	Aenderung/Datum					
Д	W.	BL 85 ermaqu	Balfoui ip, SR.	r Bea S	tty			Α	А	Pos. 8 /01.00					
Е	3	,									Bearb. 14.12.99. Gepr. 14.12.99		Stromabne. Pantograph	hmer WBL 8	25
C	;										Norm. Schunk		1-9910.496	 61	Blatt
0)											(GMH)	S10-00-4.	961	<i>02</i> 04 ві.

V

	1	,	2		3	4			5			6	7	6	7
P	os.	Mer C	nge B	A	Ein- heit	Вепеппипс			Sachnumr Normbezeicl	ner nnung	Werl	kstoff	Gewicht kg/Einheit	Bemerkung	
4	19			1	Stk	Ger. Einschraut	verschr	r. 1	1050-6-1/4 28-21-0612		Ms vernick	elt			
	50			2	Stk	Sechskantschra	ube	1	M6x20 DIN 933 20-06-0203		A2-70				
	51			4	Stk	Scheibe		1	A 6,4 DIN 125 32-06-0003		A2				
3	52			2	Stk	Sechskantmutt	er	/	M6 DIN 985 30-06-0023		A2-70				-
									30 00 0023						-
															_
															1
															+
															1
		Ana	ahen zu a	l den Menge	nspalten		Zg. St. Ausg. Ausg	1.	Aenderung/Datum						
4	WBL 85 Permaqi				-r 3.0011				os. 8 /01.00						-
E		אט, אוג								Bearb 14.12.99. S Gepr. 14.12.99 P	Santner	Stromabneh	mer WBL 8:	 5	
										Norm.		Pantograph	WBL 85	Blatt	
										Schunk Bahntechnik Salzb	(schink) GmbH	1-9910.496 510-00-49	61	04	
										SUIZDL	⊐r ⊖ Ers.1.			<i>04</i> BI.	·




1		2 3 Menge Ein- Bener							5				6	7	8	
Pos.	D	Men C	ge B	Α	Ein- heit	Benennung			Sachnummer Normbezeichnung	9		Werkst	off	kg/Einh. (fertig)	Bemerkung RC	
1				.1	Stk	Balg			Martonair M/30103	3		Neopre	n			
2				1	Stk	Zylinderhalteru	ng		Zn.Nr. 2-B14.2023	3						
3				1	Stk	Zylinderhalteru	ng		Zn.Nr. 1-B14.2024	-						
4				1	Stk	Gelenk			Zn.Nr. 4-B14.2326	5						
5				1	Stk	Verschraubung			GE12-LR 1/2"							
6				1	Stk	Gelenk			Zn.Nr. 4-B14.2327	7						
7				1	Stk	Deckel			Zn.Nr. 3-B14.2325	5						
8				1	Stk	Deckel (Ansch	luss)		Zn.Nr. 3-B14.2374	1						
9				3	Stk	Lagerachse			Zn.Nr. 4-B14.2328	3						
10				2	Stk	Gleitlager			1015 DU-B			Bronce				
11				6	Stk	Bundbuchse			BB 1012 DU-B			Bronce				
12				3	Stk	Splint			3x25 DIN94			1.4571				
13				8	Stk	Sechskantmutt	ter		M10 DIN985	5		A2				
14				1	Stk	Gewindestift			M8x20 DIN5	551		A2				
15				1	Stk	Hoehenanschla	ıg		Zn.Nr. 4-B14.2031							
	Angal	en zu (den Men	genspalt	en		Zg. Ausg	St. Zust.	Aenderung/Datum							
АВ	Balgant	rieb														
В										Gepr.	.10.91 P	eter	Balgantrieb			
С										Norm S	hun	$\frac{1}{k}$	1-B14.2022,			Blatt
D										1	echnik Gn		. 51112022	,		01 01 ві.



	1	2 Menge os. D C B				3	4			5	6	7	8	
	Pos.	1 - 1			l a	Einh.	Benennung			Sachnummer	Werkstoff	kg/Einh.	Bemerkung RC	
	1			ט	1	Stk	Schaltschrank control box co	mpl.	MTPL	55-51-0002				
	2				1	Stk	Druckluftfilter Kondensatabso		er	EAF 3000 - F2 D 55-15-0012				
	3				1	Stk	Druckregler Pressure regula			EIR 402–F02–P–L 55–01–0012				
	4				1	Stk	Drosselventil Throttle valve			ED 1/6 STK 5567/3 55-21-0012				
	5				1	Stk	Sicherheitsvent Security valve	: <i>il</i>		C 10 A.1301.1 G1/2° SV 12 3-6bar Viton/ 70 140 55-53-0014				
	6				1	Stk	T—Stück T—screw joint			2070-1/4-1/4 28-36-1212				
	7				3	Stk	Doppelnippel Screw joint			1/4" T12 872 28-29-1212	Messing vernickelt Messing vernickelt			
	8				4	Stk	Scheibe Washer			A 17 DIN 125 32-17-0003	A2			
	9				4	Stk	Schottnippel Reduction			dwg.no. 4-915.4097 11-09-4097				/
7	10				4	Stk	Rohrmutter Nut			A R 3/8" DIN 431 30-13-0093	A2			
	11				4	Stk	Gerade Versch Screw joint		ung	1511–10/8–1/4" 28–20–1012	Messing vernickelt Messing vernickelt			
	12				0.4	m	Druckluftschlau air hose	ıch		10/8 T15516 29-04-1008	PA schwarz PA schwarz			
	13				6	Stk	Scheibe Washer			A6 DIN 125 32-06-0003	A2			
	14				4	Stk	Sechskantmutt Hex nut			M6 DIN 985 30-06-0023	A2-70			
	15				2	Stk	Sechskantschro Hex screw	aube		M6x70 DIN 931 21-06-0703	A2-70			
	16				1	Stk	Distanzrohr Distance tube			dwg.no. 4-V15.4363 10-05-4363				
		Angab	en zu	den Men	genspalt	en		Zg. Ausg	St. Zust.	Aenderung/Datum				
	A	WBL 85	Balfo	ur Bea	tty, Pe	ermaq	guip, SRS							
	В									Bearb. 13.12.99 St Gepr. 13.12.99 Po	antner ordeller Ventilsteuer Pneumatic	rung control		
	С								\vdash	Norm	1-9915.498	35	BI	att
	D									Schunk Bahntechnik Wener Bundestraße 21.53	S10-05-49			<i>01</i> <i>02</i> ві.
										morror Surrossituate 21, 40	er immund			

		2			3	4			5	6	7	8	
os.		C	م ا	۱ ۸	Einh.	Benennung			Sachnummer	Werkstoff	kg/Einh.	Bemerkung RC	
7	D			2	Stk	Hex screw	aube)	M6x16 DIN 933 20-06-0163	A2-70			
8				_	_				_				
9				1	Stk	Kontermutter Nut			G 1/2" LV 42.8006 28-15-0014	Messing vernickelt			
0				1	Stk	Schalldämpfer Filter			7010-1/2 55-14-0014				
1				1	Stk	Mounting angle ii	ıkl. Sch ncl. sc	nrauben crews	B 340				
2				_	_	to be left			_				
3				1	Stk	lock insert			55-51-0004	Zink-Druckguß			
4				1	Stk	Reduziernippel screw joint			2521-1/4-1/2 28-34-1214	Messing vernickelt			
													_/
								, ,					
_	Angab	en zu	den Men	genspalt	ten		Zg. Ausg	St. Zust.	Aenderung/Datum				
W.	BL 85	Balfo	ur Bed	itty, Pe	ermaç	uip, SRS							
									Gepr. 13.12.99 F	Pardeller Ventilsteu Pneumatid	erung c control		
											985	Blatt	
									Bahntechnik Wener Bundesstraße 21, 1	GmbH 300 Hallwang	1300		2 2 Bl.
	7 8 9 9 0 0 1 1 2 2 2 3 3 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4	7	Angaben zu WBL 85 Balfo	Angaben zu den Men WBL 85 Balfour Bed	Angaben zu den Mengenspalt WBL 85 Balfour Beatty, Page A 2 B A 2 B A 2 C B A 4 C C B A 7 C C B A 7 C C B A 7 C C B A 7 C C B A 7 C C B A 7 C C B A 7 C C B A 7 C C B A 7 C C C B A 7 C C C B A 7 C C C C B A 7 C C C C C C C C C C C C C C C C C C	D C B A Stk	Sechskantschr	Sechskantschrauber	No. No.	Menge	Second S	Second S	Seches S


JIV



	1		:	2		3	4			5			6	7	6	
	Pos.	D	Mer C	nge B	A	Ein- heit	Benennun	g		Sachnumm Normbezeich	er iung	W	erkstoff	Gewicht kg/Einheit	Bernerkung	
	1				1		Kohleschleifstü Carbonstrip	ick		dwg. no. 2-10018.5 S04-00-5021	5021					
	2				1	Stk pcs	Schleifstückträ Collectorstrips	iger uppo	rt	dwg. no. 2-9918.49 10-08-4972	972					
	3				2		Hebel Lever			dwg. no. 2-W08.49 10-08-4974	74					
	4				8		Achse Axle			dwg. no. 4-L08.497 10-15-4973	73					
	5				16	Stk pcs	Gleitlager Bushing			GFM-1214-12 40-14-1212		lglidur G				
	6				1		Scheitelrohr Pantube			dwg. no. 1-9918.49 10-08-4978	78					
	7				8	Stk pcs	Sechskantschr Hex-screw	aube	•	M6x55 DIN 931 21-06-0553		A2-70				
	8				12	Stk pcs	Sechskantmutt Hex—nut	ter		M6 DIN 985 30-06-0023		A2-70				
	9				26	Stk pcs				A 6,4 DIN 125 32-06-0003		A2				
Ħ	10				2	Stk pcs	Unterlagsfeder Underlaying sp	ring		dwg. no. 4-W28.45 10-08-4575						F
	11				2		Flachfeder Leafspring			dwg. no. 4-W08.49 10-08-4976	76					
	12				4	Stk pcs	Sechskantschr Hex—screw	aube	•	M6x20 DIN 933 20-06-0203		A2-70				
	13				2		Achse Axle			dwg. no. 4-L28.211 10-08-2118	8					
	14				2	Stk pcs	Federrolle Springroll			dwg. no. 4-1038.12 10-08-1244	244					
	15				1	Stk pcs	Sechskantschr Hex-screw	aube	•	M6x80 DIN 931 21-06-0803		A2-70				
	16				1	Stk pcs	Sechskantschr Hex-screw	aube	•	M8x25 DIN 933 20-08-0253		A2-70				
			Ang	aben zu c	len Menge	nspalten		Zg. Ausg.	St. Ausg.	Aenderung/Datum						
	A 1	Balfour	Beatty	•					Α	Pos. 1, 29,30 /01.00						
	В										Bearb <i>13.12.99</i> S Gepr. <i>13.12.99 F</i>		Wippe Panhead			
	С										Norm.	Schulk		5 <i>7</i>	Blatt	\dashv
	D										Schunk Benntechnik Benntechnik	GmbH L C G Ers.f.	S10-08-49	57	01 02	
												•			<u> </u>	

1		2	!		3	4			5			6	7	6
Pos.	D	Mer C I	ige B	l a	Ein- heit	Benennu	ng		Sachnur Normbeze	nmer chnung		Werkstoff	Gewicht kg/Einheit	Bemerkung
17				1	Stk	Sechskantmut Hex-nut	ter		M8 DIN 934 30-08-0003		A2-70)		
18				1		3/2 Wegevent 3/2 way-valv	til 1/ re 1/	/8" /8"	BRVS 3 55-30-0011					
19				3	Stk	Sechskantsch Hex-screw			M4x35 DIN 931 21-04-0353		A2-70	0		
20				6	Stk	Scheibe Washer			A4,3 DIN 125 32-04-0003		A2			
21				3	Stk	Sechskantmut Hex-nut	ter		M4 DIN 985 30-04-0023		A2-70)		
22				1	1 /		chra	ubung	1525-6/4-1/8 28-27-0611		Ms ve	rnickelt		
23				1	Stk	Blende Blind			dwg. no. 4-V15.4	979				
24				1		Ger. Verschra Srew joint	ubun	g	1511-6/4-1/8 28-20-0611		Ms ve	rnickelt		
25				1	Stk				G 1/8" A LV 42.0 28-31-0011	5004	Ms ve	rnickelt		
26				2	Stk	Bundbuchse Bushing			dwg. no. 4-L28.4 10-08-4626					
27				2	Stk	Gleitlager Bushing			GFM-1618-12 40-14-1612		Iglidur	G		
28				4	Stk	Stromband Shunt			Länge bei Montag ermitteln	e	Werks	toff		
29				2	Stk	Horn komplet Horn complet	t		dwg. no. 2-10018 S10-08-5025	.5025				
30	+			2	Stk	Wanne	-		dwg. no. 3-10018					
					pcs	Tub			10-08-5026					
		A	aben zu d	lan Manas			Zg.	St. Ausg.	Aenderung/Datum					
	Balfour			en menge	nsparten	1	Ausg	-	Pos. 1, 29,30 /01.00	2				
В										Bearb 13.12.99		Wippe		
c										Gepr. <i>13.12.99</i> Norm.		Panhead		I
							+			Schunk	(schyrk) GmbH	1-9908.45 S10-08-4	957 1957	Blatt <i>02</i>
لـــّـا										Bahntechnik Salzb	űrg	Ers.f.		<i>02</i> B


VV




	1		2			3	4				5			6	7	8	
	Pos.	D	Men C	ge B	A	Ein- heit	Benennung			Sachnum Normbezeid	mer chnung		Werkst	off	kg/Einh. (fertig)	Bemerkung RC)
	17				1	Stk	Splintbolzen ø	8		Best.Nr.12008	•						
	18				1	Stk	Scheibe			A8.4 D	IN 125		A2				
	19				1	Stk	Splint			2x20	DIN 94		A2				
	20				1	Stk	Rolle			Zg.Nr.4-KL19.	2717						
	21				1	Stk	Achse			Zg.Nr. 4-L09.	2713						
	22				1	Stk	Splint			3x25 DIN	94		A2				
	23				1	Stk	Sechskantschr	aube	•	M6x40 L	DIN 931		A2				
\																	
7																	
		Anga	ben zu	den Men	genspalt	ten		Zg. Ausg	St. Zust.	Aenderung/Datum							
	A S	SNCF E	Brives			_			1	Pos.20,24 3.9							
	В										Bea Gep	ъ. <i>28.01.94</i>	Santner	AP-J-J-J-J-J	· · · · ·		
	С										Nor	n		Niederhaltek			Blatt
	D											Schur Bahntechnik (1-KL19.270	0	-	<i>02</i> <i>02</i> Bl.
																<u> </u>	<u> </u>

1		2			3	4			5			6	7	8	
Pos.	D	Men C	ge B	l a	Ein- heit	Benennung			Sachnummer Normbezeichnung		Werkstof	f	kg/Einh. (fertig)	Bemerkung RC	
1				1	Stk	Klinkenhalter			Zg.Nr. 2-KL19.2701						
2				2	Stk	Klemme			Zg.Nr. 4-KL19.2707						
3				4	Stk	Sechskantschr	aube	,	M8x25 DIN 933		A2				
4				4	Stk	Sechskantmut	ter		M8 DIN 985		A2				
5				4	Stk	Scheibe			A 8.4 DIN 125		A2				
6				1	Stk	Klinke			Zg.Nr. 4-KL19.2708						
7				2	Stk	Bundbuchse			FMB 1012 DU						
8				1	Stk	Achse			Zg.Nr.4-L09.2712						
9				1	Stk	Sechskantschr	aube	;	M6x50 DIN 931		A2				
10				2	Stk	Sechskantmut	ter		M6 DIN 985		A2				
11				1	Stk	Bremszylinder			Best.Nr.SZ1161						
12				1	Stk	Gabelkopf kurz	?		Best.Nr.12056						
13				1	Stk	Sechskantmut	ter		M8 DIN 934		A2				
14				1	Stk	Schneidring Ø6	3		DPR 6 L/S						
15				1	Stk	Überwurfmutte	er		M6-L		verz.				
16				1	Stk	Gleitlagerbuchs	se		MB 0808		Werkstof	f			
	Angal	ben zu (den Men	genspalt	ten		Zg. Ausg	St. Zust.	Aenderung/Datum						
A S	SNCF B	Brives						1	Pos.20,24 3.94						
В									Gepr.	28.01.94 S	antner	Niederhaltek	dinke		
С									Norm	L chun	k			E	Blatt
D								\vdash		ntechnik Gn		1-KL19.270	U		<i>01</i> <i>02</i> Bl.

Г



	1		2			3	4			5			6	7	8	
	Pos. ITEM	D	Men C	ge/QTY B	A	Einheit UNIT	Benennung/DES	CRIPTI	ON	Sachnummer/Normbeze P/N	ichnung	Werksto	ff/MATERIAL	kg/Einh. kg/UNIT	Bemerkung/ RC	/NOTE
	1				1	pcs Stk	AXLE FOR FLOATIN Lagerachse f. l	G BEA _osla	RING ger	Zn.Nr. 4-L03.1979						
	2				1	pcs Stk	AXLE FOR FIXED B Lagerachse f. f	EARIN(estlo	; iger	Zn.Nr. 4-L03.1978						
	3				4	pcs Stk	BALL BEARING Rillenkugellager			6203.2RSR DIN625						
	4				2	pcs Stk	INTERNAL RETAIN Seegerring	IING F	RING	40x1.75 DIN472						
	5				2	pcs Stk	EXTERNAL RETAIL Seegerring	NING I	RING	17x1 DIN471						
	6				4	pcs Stk	COVER Abdeckscheibe			Zn.Nr. 4-L03.1980						
	7				2	pcs Stk	WASHER Scheibe			A13 DIN125		A2				
	8				2	pcs Stk	SPRING WASHEI Federring	R		A12 DIN127		A2				
	9				2	pcs Stk	HEX HEAD SCR Sechskantschro	EW		M12x80 DIN931		A2				
Ħ	10					pcs Stk	GREASE Fett			Autol Top 2000						
		Angal	oen zu	den Men	genspalt	ten		Zg. Ausg Z	St. ust.	Aenderung/Datum		'		•		
	Α ()bersch	rere/U	PPER F	FRAME			A B		Pos. 3,10/28.5.97 Sprache/23.9.97						
	В									Bearb. 2	2.9.91 P 2.9.91 S	eter antner	UPPER FRA		NG	
	С									Norm			Oberscherer			Blatt
	D										Chun technik Gm	I .	3-L03.1977			BI.
												1				51.



	1		2			3	4			5			6	7	8		
	Pos. ITEM	D	Men C	ge/QTY B	l a	Einheit UNIT	Benennung/DES	CRIPTI	ON	Sachnummer/Nor P/N	mbezeichnung	Werksto	ff/MATERIAL	kg/Einh. kg/UNIT	Bemerkung, RC	/NOTE	
	1				1	pcs Stk	AXLE FOR FIXED BI Lagerachse f. F	EARING estlo	G ager	Zn.Nr. 4-L01.1974							
	2				1	pcs Stk	AXLE FOR FLOATING Lagerachse f. L	G BEA Losla	RING ger	Zn.Nr. 4-L01.1975							
	3				4	pcs Stk	BALL BEARING Rillenkugellager			6006.2RSR DIN	625						
	4				4	pcs Stk	COVER Abdeckscheibe			Zn.Nr. 4-L01.1976							
	5				2	pcs Stk	INTERNAL RETAIN Seegerring	IING F	RING	55x2 DIN472							
	6				2	pcs Stk	EXTERNAL RETAIN Seegerring	NING	RING	30x1.5 DIN471							
	7				2	pcs Stk	HEX HEAD SCR Sechskantschra	EW ube		M20x90 DIN931		A2					
	8				2	pcs Stk	WASHER Scheibe			A21 DIN125		A2					
	9				2	pcs Stk	SPRING WASHER Federring	₹		A20 DIN127		A2					
Ħ	10				·	pcs Stk	GREASE Fett			Autol Top 2000						_	Ħ
		Angal	ben zu	den Men	genspalt	en		Zg. Ausg Z		Aenderung/Datum							
	A	Grundra	ıhmen/	BASE	FRAME			А В		Pos. 3,10/28.5.97 Sprache/23.9.97							
	В										earb. 30.8.91 P epr. 30.8.91 S	eter antner	BASE FRAM	IE BEARING			
	С									No	Schun		Basislager 3-L01.1973	ζ		Blatt	
	D										Bahntechnik Gr	I .	J-LUI.1973			BI.	



12. Annex

Pneumatic diagramm drawing no. 3-9919.4963

WBL 85-15kV Page 55

